

ZAC-30 / ZAC-30jr ZON 30-Watt Controller Amplifier

ZON[®]
Whole House
Digital Audio



ZAC-30



ZAC-30jr



The ZAC-30 (also known as the "Mini-ZAC" because of its size relative to the well known and larger ZAC-60) is designed for use in smaller rooms such as bathrooms or sunrooms. Like its bigger brother, the ZAC-30 uses the all-digital architecture pioneered by ZON.

The ZAC-30 features ZON's popular Euro-style user interface for source selection, bass, treble, loudness and EQ settings, onboard 30-watt digital stereo amplifier and a built-in infrared receiver. Like other ZON digital products it connects to the ZON system with a single CAT-6 or CAT-5e cable. Loudspeakers connect directly to the ZAC-30 by way of an installation-friendly, removable screw terminal connector.

The half-size ZAC-30 controller/amplifier is offered in two versions, one with a full-featured display and another, lower-priced model, called the ZAC-30jr for locations not requiring a display. Both versions mount in a standard single-gang trim ring.

OXMOOR[®]

Oxmoor Corporation, LLC
309 Cahaba Valley Parkway
Indian Springs, AL 35124
800.262.6898
205.982.8200
Fax: 205.982.8292
www.zonaudio.com

Specifications subject to change without notice.

ZON is a registered trademark of Oxmoor Corporation, LLC.
0406

Specifications

	ZAC-30	ZAC-30jr
Amplification		
Type	All Digital, Stereo	Same
Power	30 Watts (15W x 2) RMS @ 6 ohm	Same
Amplifier Efficiency	> 90%	Same
Frequency Response	20 Hz - 20 kHz	Same
Noise Floor	< -96 dBFS @ 1 kHz 'A' Weighted	Same
THD + N	< 0.1 % @ 1 kHz, Maximum Power < 0.05 % @ 1 Watt	Same
Loudspeaker Impedance	4 - 8 ohms	Same
Loudspeaker Connection	Plug-connected Screw Terminals (L & R x 2)	Same
Controller		
Jog Wheel	Multi-Function Shaft Encoder	Same
Jog Wheel Indicator	Virtual Pointer™ LED display	None
Graphical User Interface	High Resolution Graphical User Interface	None
Remote Control	All functions remotely controllable Compatible with ZÖN mini-remote	Same
Volume Control	Adjustable via shaft encoder Level is independent from ZAC-60 parent	Same
Source Selection	Selectable via shaft encoder or IR Remote Shares parent ZAC-60 Source	IR Remote Only Same
Input Source Naming	User Defined	None
Digital Signal Processing	Integrated, onboard	Same
Equalization	GUI & Software Selectable Presets	Software selectable only
Tone Control	GUI & Software Selectable Bass, Treble and Loudness	Software selectable only Same
Balance Control	GUI & Software Selectable	Software selectable only
IR Receiver	38 kHz pass through to selected input	Same
Paging	Receives pages from ZÖN system Does not originate pages	Same
Connections		
Wiring Specifications	CAT-6 or CAT-5e Class II, 4 twisted pair (100 ohm Impedance)	Same
Connection	8P8C Modular Jack from Expansion Port on ZAC-60 Series VA0105 and above	Same
Termination Method	EIA 568-A or 568-B	Same
Mounting		
Mount Method	Single gang low voltage mounting ring (User provided)	Same
Other		
Agency Approvals	UL, CE, FCC (Part 15 Class B)	Same
Front Panel Dimensions	2 13/16" W x 4 1/2" H	Same
Depth Behind Wall	2 1/2" (assumes 1/2" wallboard thickness)	Same
Colors	ZÖN Standard Color Palette	Same
Shipping Weight	Approximately 1 Pound	Same

All specifications subject to change without notice